11. Click on the + (plus sign) in front of the **"Infrared devices"**, one **"USB-Infrared Adapter"** should be displayed.

For Windows® Vista

1. With the computer powered on, connect the USB to IrDA adapter to an available USB port. Windows should automatically detect a new device, and prompt you for driver installation. Please select **Locate and install Driver Software**.
2. Windows will search online for driver updates for the adapter, and notify you that it couldn't locate suitable software. Click on **Browse my computer for Driver Software**. Insert the driver CD into the CD/DVD-ROM drive. On the window that follows, click the **Browse** button, then navigate to and select the **\MCS7780\Vista32** folder on the driver CD, then click **OK** to designate the location. Click on **Next** to begin installation.
3. Once the necessary files have been installed, you will be notified that **The software for this device has been successfully installed**. Click **Close**.
4. Open "Device Manager" under System Properties.
5. Click on the + (plus sign) in front of the **"Infrared devices"**, one **"MosChip 7780-USBFIR Adapter"** should be displayed.

USB to IrDA Adapter

User Manual

Ver. 3.00

All brand names and trademarks are properties of their Respective owners.

Features

- Compliant with the Standard Specification of USB 1.1 and 2.0
- Full Compliance to IrDA 1.4
- Powered from USB port, no adapter required
- IrDA Data Rates from 2.4 Kbps to 115.2 Kbps in SIR mode
- Supports MIR (Medium IR) at 1.152 Mbps
- Supports FIR (Fast IR) mode with Data Rate of 4 Mbps
- Supports Windows® 2000, XP/2003 32/64 bit, Vista 32/64bit

System Requirements

- Windows® 2000, XP, 2003, Vista
- Available USB port

Package Contents

- 1 x USB to IrDA adapter
- 1 x Driver CD
- 1 x User's Manual

Optional Accessories

- USB Cable

Driver Installation

For Windows® 2000/XP/Server 2003

1. Don't plug in the USB to IrDA adapter to the USB port of your computer.
2. Please insert the CD driver bound with USB to IrDA adapter into your CD-ROM Drive.
3. At the Windows desktop click **Start**, then **Run**.
4. Type **D:\MCS7780\IRSetup.exe**, then click **OK**.
   (Change **D:** to match your CD-ROM drive letter)
5. Follow the on-screen instructions to complete the installation.
6. Plug in the USB to IrDA adapter to the USB port of your computer.
7. Windows should detect the new USB device, and a Found New Hardware wizard window appears. Click on **Next** to continue.
8. Click on **Finish** to close the wizard.
9. When Windows desktop is displayed, the driver installation is complete.
10. Open "Device Manager" under System Properties.